

DISPLAY Elektronik GmbH

DATA SHEET

LCD MODULE

DEM 128064H FGH-PW

Product specification

Version : 7

09/AUG/2006

GENERAL SPECIFICATION

MODULE NO. :

DEM 128064H FGH-PW

CUSTOMER P/N

VERSION NO.	CHANGE DESCRIPTION	DATE
0	ORIGINAL VERSION	15/03/2005
1	CHANGED SERIES	09/05/2005
2	CHANGED MODULE DRAWING	25/05/2005
3	CHANGED BACKLIGHT ELECTRICAL/OPTICAL SPECIFICATIONS	29/06/2005
4	CHANGED PCB DRAWING AND DESCRIPTION	01/11/2005
5	CHANGED PCB DRAWING AND DESCRIPTION	07/11/2005
6	ADDED VERSION	07/08/2006
7	MODIFY CONTRAST REGULATION	09/08/2006

PREPARED BY : HZZ

DATE: 09/08/2006

APPROVED BY: MH

DATE: 22/09/2006

CONTENTS

1. FUNCTIONS & FEATURES ----- 2

2. MECHANICAL SPECIFICATIONS ----- 2

3. EXTERNAL DIMENSIONS----- 3

4. BLOCK DIAGRAM ----- 3

5. PIN ASSIGNMENT ----- 4

6. POWER SUPPLY ----- 4

7. PCB DRAWING----- 5

7.1 PCB DESCRIPTION ----- 5

7.2 EXAMPLE APPLICATION ----- 6

8. ABSOLUTE MAXIMUM RATINGS ----- 6

9. ELECTRICAL CHARACTERISTICS ----- 7

10. BACKLIGHT ELECTRICAL/OPTICAL SPECIFICATIONS ----- 9

11. PRECAUTION FOR USING LCM ----- 10

12. LCD MODULES HANDLING PRECAUTIONS ----- 12

13. OTHERS ----- 12

1. FUNCTIONS &FEATURES

- LCD TYPE:


MODULE NAME	LCD TYPE	REMARK
DEM 128064H FGH-PW	FSTN Transflective Positive Mode	RoHS conform

- LCD-Controller/LCD-Driver : T6963C + S6B0086 (or equivalent)
- Glass Thickness : 1.1mm
- Viewing Direction : 6 o'clock
- Driving Scheme : 1/64Duty, 1/9 Bias
- Power Supply for logic : 5.0 Volt (typ.)
- Backlight Color : White, Lightguide (3 LEDs)
- Display Content : 128 x 64 Dots
- V_{LCD} : 12.6 Volt (typ.)
- Operation temperature : -20°C to +70°C
- Storage temperature : -25°C to +75°C
- Contrast Regulation : External + Internal


2. MODULE ARTWORK

- Module Size : 78.0 x 70.0 x 12.6 mm
- Viewing Area : 62.0 x 44.0 mm
- Active Area : 56.27 x 38.35 mm
- Dot Pitch : 0.44 x 0.60 mm
- Dot Size : 0.39 x 0.55 mm
- Dot Gap : 0.05 mm

3. EXTERNAL DIMENSIONS



4. BLOCK DIAGRAM




5. PIN ASSIGNMENT


NO.	SYMBOL	FUNCTION
1	VEE	Power supply output for LCD
2	VSS	Ground (0V)
3	VDD	Power Supply(+5V)
4	V0	Power Supply for LCD Drive
5	/WR	Data write. Write data to controller T6963C when “L”
6	/RD	Data read. Read data from controller T6963C when “L”
7	/CE	Chip enable of controller when “L”
8	C/ D	Command/Data read/write. “H” for command read/write and “L” for data read/write
9	/RST	Controller reset when “L”
10	DB0	Data input/output(LSB)
11	DB1	Data input/output
12	DB2	Data input/output
13	DB3	Data input/output
14	DB4	Data input/output
15	DB5	Data input/output
16	DB6	Data input/output
17	DB7	Data input/output(MSB)
18	FS	Font select. “H” for 6x8 font & “L” for 8x8 font
19	LED+(A)	Anode of LED backlight (using integrated resistors)
20	LED - (K)	Cathode of LED backlight (using integrated resistors)

6. POWER SUPPLY


➤ **Mode(Internal contrast regulation)-J7 is close**



➤ **Mode(external contrast regulation)-J7 is open**



7. PCB DRAWING



7.1 PCB DESCRIPTION:

7-1-1.The polarity of the pin 19 and the pin 20:

symbol	symbol state	J3,J5	J6, J4	LED Polarity	
				19 Pin	20 Pin
J6,J4	Each solder-bridge	Each closed	Each open	Anode	Cathode
J3,J5	Each solder-bridge	Each open	Each closed	Cathode	Anode

Note: In application module, J3=J5 =closed, J4=J6=open.

7-1-2. The J1 is metal-bezel GND to module GND.

Note: In application module, J1=closed.

7-1-3.The LED resistor should be bridged when J2 is closed.

Note: In application module, J2=open.

7-1-4.The module use internal contrast regulation when J7 is closed.


Note: In application module, J7 is open. To use integrated potentiometer please close J7.

7-1-5.The R8, R9, R10 and R11 are the LED resistors.

Note: In application module, R9=470hm R8 = R10= R11=Not used.

7.2 Example application

7-2-1. The LED resistor should be bridged as following.



7-2-2. The 19 pin is the anode and the 20 pin is the cathode as following.



7-2-3. The metal-bezel is on ground as following.



7-2-4. The module use internal contrast regulation as following.



8. ABSOLUTE MAXIMUM RATINGS ($V_{SS}=0V$, $T_a=25^{\circ}C$)

PARAMETER	SYMBOL	RATING	UNIT
Supply Voltage (Logic)	V_{DD}	-0.3 to 7.0	V
Input voltage	V_{IN}	-0.3 to $V_{DD} + 0.3$	V
Operating Temperature	T_{opr}	-20 to +70	$^{\circ}C$
Storage Temperature	T_{stg}	-25 to +75	$^{\circ}C$

9. ELECTRICAL CHARACTERISTICS


1). DC Characteristics

Ta=25°C, VSS=0V

Parameter	Symbol	Conditions	Min.	Typ.	Max.	Units
Supply Voltage (Logic)	$V_{DD}-V_{SS}$	-	4.5	5.0	5.5	V
High Level Input Voltage	V_{IH}	$V_{DD}=5.0V\pm 10\%$	$V_{DD}-2.2$	-	V_{DD}	V
Low Level Input Voltage	V_{IL}	$V_{DD}=5.0V\pm 10\%$	0	-	0.8	V
High Level Output Voltage	V_{OH}	$I_{OH}=0.75mA$	$V_{DD}-0.3$	-	V_{DD}	V
Low Level Output Voltage	V_{OL}	$I_{OL}=0.75mA$	0	-	0.3	V
Current Consumption(Operating)	$I_{DD(1)}$	$V_{DD}=5.0V$ $f_{OSC}=3.0\text{ MHz}$	-	3.3	6.0	mA
Current Consumption(Halt)	$I_{DD(2)}$	$V_{DD}=5.0V$			3	μA


2). AC Characteristics

Parameter	Symbol	Min.	Max.	Units
C/D Setup Time	t_{CDS}	100	-	ns
C/D Hold Time	t_{CDH}	10	-	ns
CE, RD, WR Pulse Width	t_{CE}, t_{RD}, t_{WR}	80	-	ns
Data Setup Time	t_{DS}	80	-	ns
Data Hold Time	t_{DH}	40	-	ns
Access Time	t_{ACC}	-	150	ns
Output Hold Time	t_{OH}	10	50	ns




3). Power Supply ON/OFF Sequence


● ON Sequence



● OFF Sequence



● Reset Sequence



Please maintain the above sequence when turning on and off the power supply of the module.
If VEE is supplied to the module while internal alternate signal for LCD driving (M) is unstable or RESET is active, DC component will be supplied to the LCD panel. This may cause damage to the LCD module.

11. PRECAUTION FOR USING LCM**1. LIQUID CRYSTAL DISPLAY (LCD)**

LCD is made up of glass, organic sealant, organic fluid, and polymer based polarizer. The following precautions should be taken when handling,

- (1). Keep the temperature within range of use and storage. Excessive temperature and humidity could cause polarization degradation, polarizer peel off or bubble.
- (2). Do not contact the exposed polarizer with anything harder than an HB pencil lead. To clean dust off the display surface, wipe gently with cotton, chamois or other soft material soaked in petroleum benzin.
- (3). Wipe off saliva or water drops immediately. Contact with water over a long period of time may cause polarizer deformation or color fading, while an active LCD with water condensation on its surface will cause corrosion of ITO electrodes.
- (4). Glass can be easily chipped or cracked from rough handling, especially at corners and edges.
- (5). Do not drive LCD with DC voltage.

2. Liquid Crystal Display modules**2.1 Mechanical considerations**

LCM are assembled and adjusted with a high degree of precision. Avoid excessive shocks and do not make any alterations or modifications. The following should be noted.

- (1). Do not tamper in any way with the tabs on the metal frame
- (2). Do not modify the PCB by drilling extra holes, changing its outline, moving its components or modifying its pattern.
- (3). Do not touch the elastomer connector, especially insert an backlight panel (for example, EL).
- (4). When mounting a LCM make sure that the PCB is not under any stress such as bending or twisting. Elastomer contacts are very delicate and missing pixels could result from slight dislocation of any of the elements.
- (5). Avoid pressing on the metal bezel, otherwise the elastomer connector could be deformed and lose contact, resulting in missing pixels.

2.2. Static Electricity

LCM contains CMOS LSI's and the same precaution for such devices should apply, namely

- (1). The operator should be grounded whenever he/she comes into contact with the module. Never touch any of the conductive parts such as the LSI pads, the copper leads on the PCB and the interface terminals with any parts of the human body.
- (2). The modules should be kept in antistatic bags or other containers resistant to static for storage.
- (3). Only properly grounded soldering irons should be used.
- (4). If an electric screwdriver is used, it should be well grounded and shielded from commutator sparks.
- (5). The normal static prevention measures should be observed for work clothes and working benches; for the latter conductive (rubber) mat is recommended.
- (6). Since dry air is inductive to static, a relative humidity of 50-60% is recommended.

2.3. Soldering

- (1). Solder only to the I/O terminals.
- (2). Use only soldering irons with proper grounding and no leakage.
- (3). Soldering temperature: $280^{\circ}\text{C} \pm 10^{\circ}\text{C}$
- (4). Soldering time: 3 to sec.
- (5). Use eutectic solder with resin flux fill.
- (6). If flux is used, the LCD surface should be covered to avoid flux spatters.
Flux residue should be removed afterwards.

2.4 Operation

- (1). The viewing angle can be adjusted by varying the LCD driving voltage V0.
- (2). Driving voltage should be kept within specified range; excess voltage shortens display life.
- (3). Response time increases with decrease in temperature.
- (4). Display may turn black or dark blue at temperatures above its operational range; this is (however not pressing on the viewing area) may cause the segments to appear “fractured”.
- (5). Mechanical disturbance during operation (such as pressing on the viewing area) may cause the segments to appear “fractured”.

2.5 Storage

If any fluid leaks out of a damaged glass cell, wash off any human part that comes into contact with soap and water. Never swallow the fluid. The toxicity is extremely low but caution should be exercised at all the time.

2.6 Limited Warranty

Unless otherwise agreed between DISPLAY and customer, DISPLAY will replace or repair any of its LCD and LCM which is found to be defective electrically and visually when inspected in accordance with DISPLAY acceptance standards, for a period on one year from date of shipment. Confirmation of such date shall be based on freight documents. The warranty liability of DISPLAY is limited to repair and/or replacement on the terms set forth above. DISPLAY will not responsible for any subsequent or consequential events.

12. LCD MODULES HANDLING PRECAUTIONS

- Please remove the protection foil of polarizer before using.
- The display panel is made of glass. Do not subject it to a mechanical shock by dropping it from a high place, etc.
- If the display panel is damaged and the liquid crystal substance inside it leaks out, do not get any in your mouth. If the substance come into contact with your skin or clothes promptly wash it off using soap and water.
- Do not apply excessive force to the display surface or the adjoining areas since this may cause the color tone to vary.
- The polarizer covering the display surface of the LCD module is soft and easily scratched. Handle this polarize carefully.
- To prevent destruction of the elements by static electricity, be careful to maintain an optimum work environment.
 - Be sure to ground the body when handling the LCD module.
 - Tools required for assembly, such as soldering irons, must be properly grounded.
 - To reduce the amount of static electricity generated, do not conduct assembly and other work under dry conditions.
 - The LCD module is coated with a film to protect the display surface. Exercise care when peeling off this protective film since static electricity may be generated.
- Storage precautions
When storing the LCD modules, avoid exposure to direct sunlight or to the light of fluorescent lamps. Keep the modules in bags designed to prevent static electricity charging under low temperature / normal humidity conditions (avoid high temperature / high humidity and low temperatures below 0°C). Whenever possible, the LCD modules should be stored in the same conditions in which they were shipped from our company.

13. OTHERS

- Liquid crystals solidify at low temperature (below the storage temperature range) leading to defective orientation of liquid crystal or the generation of air bubbles (black or white). Air bubbles may also be generated if the module is subjected to a strong shock at a low temperature.
- If the LCD modules have been operating for a long time showing the same display patterns may remain on the screen as ghost images and a slight contrast irregularity may also appear. Abnormal operating status can be resumed to be normal condition by suspending use for some time. It should be noted that this phenomena does not adversely affect performance reliability.
- To minimize the performance degradation of the LCD modules resulting from caused by static electricity, etc. exercise care to avoid holding the following sections when handling the modules:
 - Exposed area of the printed circuit board
 - Terminal electrode sections