

Product Brief – JN5139


IEEE802.15.4 and ZigBee Wireless Microcontrollers

Overview

The JN5139 is a low power, low cost wireless microcontroller suitable for IEEE802.15.4 and ZigBee applications. Each device integrates a 32-bit RISC processor, with a fully compliant 2.4GHz IEEE802.15.4 transceiver, 192kB of ROM, 96kB RAM and a rich mixture of analogue and digital peripherals.

The cost-sensitive ROM/RAM architecture supports the storage of system software, including protocol stacks, routing tables and application code/data. Each device integrates hardware MAC and AES encryption accelerators, power saving and timed sleep modes, and mechanisms for security key and program code encryption. These features all make for a highly efficient, low power, single chip wireless microcontroller for battery-powered applications.

Block Diagram



Design Flexibility

Benefits

- Single chip integrates transceiver and microcontroller for wireless sensor networks
- Cost sensitive ROM/RAM architecture, meets needs for volume application
- System BOM is low in component count and cost
- Hardware MAC ensures low power consumption and low processor overhead
- Extensive user peripherals
- Pin compatible with JN5121 for easy migration

Applications

- Robust and secure low power wireless applications
- Wireless sensor networks, particularly IEEE802.15.4 and ZigBee systems
- Home and commercial building automation
- Remote Controls
- Toys and gaming peripherals
- Industrial systems
- Telemetry and utilities (e.g. AMR)

Features: Transceiver

- 2.4GHz IEEE802.15.4 compliant
- 128-bit AES security processor
- MAC accelerator with packet formatting, CRCs, address check, auto-acks, timers
- Integrated power management and sleep oscillator for low power
- On-chip power regulation for 2.2V to 3.6V battery operation
- Deep sleep current 0.2μA
- Sleep current with active sleep timer 1.3µA
- Needs minimum of external components (< US\$1 cost)
- Rx current 34mA
- Tx current 34mA
- Receiver sensitivity -97dBm
- Transmit power +3dBm

Features: Microcontroller

- 32-bit RISC processor sustains 32MIPs with low power
- 192kB ROM stores system code, including protocol stack
- 96kB RAM stores system data and optionally bootloaded program code
- 48-byte OTP eFuse, stores MAC ID on-chip, offers AES based code encryption feature
- 4-input 12-bit ADC, 2 11-bit DACs, 2 comparators
- 2 Application timer/counters,
 3 system timers
- 2 UARTs (one for debug)
- SPI port with 5 selects
- 2-wire serial interface
- Up to 21 GPIO

Industrial temperature range (-40 °C to +85 °C) 8x8mm 56-lead QFN

Lead-free and RoHS compliant



Battery Optimisation

To maximise battery life, devices support a series of power management and sleep modes. Used effectively, these will allow a batteries life expectancy for a typical remote sensing application, to be of the order of a few years.


Power Saving Mode	Typical Current
Deep sleep	0.2μΑ
Sleep: wakeup on I/O or timer event	1.3μΑ
Sleep: wakeup on I/O or timer event and 96kB RAM retained	3.3μΑ

Wireless Protocol Stacks in ROM

Two standard ROM configurations are available that integrate IEEE802.15.4b and ZigBee protocol stacks. The JN5139-000 integrates IEEE802.15.4b for development of proprietary systems, and the JN5139-Z01 integrates the ZigBee protocol stack, this supporting co-ordinator, router and end device configurations. Custom ROM masks will support the integration of user code into ROM, attractive to higher volume applications.

Application Diagram

The JN5139 device requires a minimum of external components to support wireless applications; a crystal, some decoupling components and printed antenna are all that is required for the lowest cost bill of materials and smallest size (an external bootloader flash may be used for optional program code storage).



Evaluation Kits

To assist users with the development of wireless sensor networks, Jennic provide a series of Evaluation Kits. These contain everything that is needed to carry out complete development and test, and include controller and sensor boards, interface dongle to connect with a PC and a Software Developer Kit (SDK).

The SDK provides a comprehensive suite of tools to facilitate the development of application code. The kit includes a C compiler, graphical and text debuggers, assembler, linker and flash programmer. A set of libraries provides a simple Application Programming Interface (API) to drive the peripherals of the controller and sensor boards.



Corporate Headquarters Furnival Street Sheffield S1 4QT

United Kingdom

Tel +44 (0)114 2812655 Fax +44 (0)114 2812951 E-mail info@jennic.com **Taiwan Sales Office**

19F-1, 182, Sec.2 Tun Hwa S. Road Taipei 106 Taiwan

Tel +886 2 2735 7357 Fax +886 2 2739 5687 E-mail info@tw.jennic.com Japan Sales Office

Osakaya building 4F 1-11-8 Higashigotanda Shinagawa-ku Tokyo 141-0022, Japan

Tel +81 3 5449 7501 Fax +81 3 5449 0741

info@jp.jennic.com

United States Sales Office

1060 First Avenue, Suite 400 King of Prussia PA 16406 USA

Tel +1 610 768 8071 Fax +1 484 971 5015 E-mail info@us.jennic.com

E-mail