

#### STS25N3LLH6

# N-channel 30 V, 0.0025 Ω, 22 A, SO-8 STripFET™ VI DeepGATE™ Power MOSFET

Preliminary Data

#### **Features**

Туре	V <sub>DSS</sub>	R <sub>DS(on)</sub> max	I <sub>D</sub>
STS25N3LLH6	30 V	$0.0032~\Omega$	22 A

- R<sub>DS(on)</sub> \* Q<sub>g</sub> industry benchmark
- Extremely low on-resistance R<sub>DS(on)</sub>
- High avalanche ruggedness
- Low gate drive power losses
- Very low switching gate charge

#### **Application**

■ Switching applications



This product utilizes the 6<sup>th</sup> generation of design rules of ST's proprietary STripFET<sup>TM</sup> technology, with a new gate structure. The resulting Power MOSFET exhibits the lowest  $R_{DS(on)}$  in a standard package, that makes it suitable for the most demanding DC-DC converter applications, where high power density has to be achieved.




Figure 1. Internal schematic diagram




Table 1. Device summary

Order code	Marking	Packag	Packaging
STS25N3LLH6	25G3L	SO-8	Tape and reel

Contents STS25N3LLH6

#### **Contents**

1	Electrical ratings	3
2	Electrical characteristics	4
3	Test circuit	6
4	Package mechanical data	8
5	Revision history	10

STS25N3LLH6 Electrical ratings

## 1 Electrical ratings

Table 2. Absolute maximum ratings

Symbol	Parameter	Value	Unit
V <sub>DS</sub>	Drain-source voltage (V <sub>GS</sub> = 0)	30	V
V <sub>GS</sub> <sup>(1)</sup>	Gate-source voltage	± 20	V
I <sub>D</sub>	Drain current (continuous) at T <sub>C</sub> = 25 °C	22	Α
I <sub>D</sub>	Drain current (continuous) at T <sub>C</sub> =100 °C	13.7	Α
I <sub>DM</sub> <sup>(2)</sup>	Drain current (pulsed)	88	Α
P <sub>TOT</sub>	Total dissipation at T <sub>C</sub> = 25 °C	2.7	W
T <sub>J</sub> T <sub>stg</sub>	Operating junction temperature Storage temperature	-55 to 150	

<sup>1.</sup> Continuous mode

Table 3. Thermal resistance

	Symbol	Parameter	Value	Unit
ĺ	R <sub>thj-amb</sub> (1)	Thermal resistance junction-ambient	47	°C/W

<sup>1.</sup> When mounted on FR-4 board of 1inch², 2oz Cu, t < 10 sec

Table 4. Avalanche data

Symbol	Parameter	Value	Unit
I <sub>AV</sub>	Not-repetitive avalanche current	TBD	Α
E <sub>AS</sub>	Single pulse avalanche energy (starting Tj=25 °C, I <sub>D</sub> =I <sub>AV</sub> )		mJ

<sup>2.</sup> Pulse width limited by safe operating area

Electrical characteristics STS25N3LLH6

### 2 Electrical characteristics

 $(T_{CASE} = 25 \, ^{\circ}C \text{ unless otherwise specified})$ 

Table 5. On/off states

Symbol	Parameter	Test conditions	Min.	Тур.	Max.	Unit
V <sub>(BR)DSS</sub>	Drain-source breakdown voltage	$I_D = 250 \ \mu A, \ V_{GS} = 0$	30			٧
I <sub>DSS</sub>	Zero gate voltage drain current (V <sub>GS</sub> = 0)	$V_{DS}$ = Max rating, $V_{DS}$ = Max rating @125 °C			1 10	μ <b>Α</b> μ <b>Α</b>
I <sub>GSS</sub>	Gate body leakage current (V <sub>DS</sub> = 0)	V <sub>GS</sub> = ±20 V			±100	nA
V <sub>GS(th)</sub>	Gate threshold voltage	$V_{DS} = V_{GS}, I_D = 250 \mu A$	1			V
R <sub>DS(on)</sub>	Static drain-source on resistance	$V_{GS}$ = 10 V, $I_{D}$ = 15 A $V_{GS}$ = 4.5 V, $I_{D}$ = 15 A		0.0025 0.0042	0.0032 TBD	Ω

Table 6. Dynamic

Symbol	Parameter	Test conditions	Min.	Тур.	Max.	Unit
C <sub>iss</sub> C <sub>oss</sub> C <sub>rss</sub>	Input capacitance Output capacitance Reverse transfer capacitance	V <sub>DS</sub> =25 V, f=1 MHz, V <sub>GS</sub> =0		2100 400 170		pF pF pF
Q <sub>g</sub> Q <sub>gs</sub> Q <sub>gd</sub>	Total gate charge Gate-source charge Gate-drain charge	$V_{DD}$ =15 V, $I_{D}$ = 22 A $V_{GS}$ =4.5 V Figure 8		16 TBD TBD	TBD	nC nC nC
R <sub>G</sub>	Gate Input Resistance	f=1 MHz Gate DC Bias = 0 Test signal level = 20 mV open drain		TBD		Ω

Table 7. Switching times

Symbol	Parameter	Test conditions	Min.	Тур.	Max.	Unit
$\begin{array}{c} t_{\rm d(on)} \\ t_{\rm r} \\ t_{\rm d(off)} \\ t_{\rm f} \end{array}$	Turn-on delay time Rise time Turn-off delay time Fall time	$V_{DD}$ =15 V, $I_{D}$ = 11 A, $R_{G}$ =4.7 $\Omega$ , $V_{GS}$ =4.5 V Figure 2		TBD TBD TBD TBD		ns ns ns ns

Table 8. Source drain diode

Symbol	Parameter	Test conditions	Min	Тур.	Max	Unit
I <sub>SD</sub>	Source-drain current				22	Α
I <sub>SDM</sub> <sup>(1)</sup>	Source-drain current (pulsed)				88	Α
V <sub>SD</sub> <sup>(2)</sup>	Forward on Voltage	I <sub>SD</sub> = 22 A, V <sub>GS</sub> =0			1.1	V
t <sub>rr</sub> Q <sub>rr</sub> I <sub>RRM</sub>	Reverse recovery time Reverse recovery charge Reverse recovery current	$I_{SD}$ = 22 A, di/dt = 100 A/ $\mu$ s, $V_{DD}$ =20 V, Tj=150 °C Figure 4		TBD TBD TBD		ns nC A

<sup>1.</sup> Pulse width limited by safe operating area

<sup>2.</sup> Pulsed: pulse duration=300  $\mu s$ , duty cycle 1.5%

Test circuit STS25N3LLH6

#### 3 Test circuit

Figure 2. Switching times test circuit for resistive load

Figure 3. Gate charge test circuit




Figure 4. Test circuit for inductive load switching and diode recovery times

Figure 5. Unclamped inductive load test circuit





Figure 6. Unclamped inductive waveform


Figure 7. Switching time waveform



577

STS25N3LLH6 Test circuit

Figure 8. Gate charge waveform




## 4 Package mechanical data

In order to meet environmental requirements, ST offers these devices in different grades of ECOPACK® packages, depending on their level of environmental compliance. ECOPACK® specifications, grade definitions and product status are available at: www.st.com. ECOPACK® is an ST trademark.

#### **SO-8 MECHANICAL DATA**

DIM		mm.			inch	
DIM.	MIN.	TYP	MAX.	MIN.	TYP.	MAX.
Α			1.75			0.068
a1	0.1		0.25	0.003		0.009
a2			1.65			0.064
a3	0.65		0.85	0.025		0.033
b	0.35		0.48	0.013		0.018
b1	0.19		0.25	0.007		0.010
С	0.25		0.5	0.010		0.019
c1			45 (	(typ.)		
D	4.8		5.0	0.188		0.196
E	5.8		6.2	0.228		0.244
е		1.27			0.050	
e3		3.81			0.150	
F	3.8		4.0	0.14		0.157
L	0.4		1.27	0.015		0.050
М			0.6			0.023
S		•	8 (n	nax.)	•	•



577

Revision history STS25N3LLH6

## 5 Revision history

Table 9. Document revision history

Date	Revision	Changes
27-Jan-2009	1	First release

#### Please Read Carefully:

Information in this document is provided solely in connection with ST products. STMicroelectronics NV and its subsidiaries ("ST") reserve the right to make changes, corrections, modifications or improvements, to this document, and the products and services described herein at any time, without notice.

All ST products are sold pursuant to ST's terms and conditions of sale.

Purchasers are solely responsible for the choice, selection and use of the ST products and services described herein, and ST assumes no liability whatsoever relating to the choice, selection or use of the ST products and services described herein.

No license, express or implied, by estoppel or otherwise, to any intellectual property rights is granted under this document. If any part of this document refers to any third party products or services it shall not be deemed a license grant by ST for the use of such third party products or services, or any intellectual property contained therein or considered as a warranty covering the use in any manner whatsoever of such third party products or services or any intellectual property contained therein.

UNLESS OTHERWISE SET FORTH IN ST'S TERMS AND CONDITIONS OF SALE ST DISCLAIMS ANY EXPRESS OR IMPLIED WARRANTY WITH RESPECT TO THE USE AND/OR SALE OF ST PRODUCTS INCLUDING WITHOUT LIMITATION IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE (AND THEIR EQUIVALENTS UNDER THE LAWS OF ANY JURISDICTION), OR INFRINGEMENT OF ANY PATENT, COPYRIGHT OR OTHER INTELLECTUAL PROPERTY RIGHT.

UNLESS EXPRESSLY APPROVED IN WRITING BY AN AUTHORIZED ST REPRESENTATIVE, ST PRODUCTS ARE NOT RECOMMENDED, AUTHORIZED OR WARRANTED FOR USE IN MILITARY, AIR CRAFT, SPACE, LIFE SAVING, OR LIFE SUSTAINING APPLICATIONS, NOR IN PRODUCTS OR SYSTEMS WHERE FAILURE OR MALFUNCTION MAY RESULT IN PERSONAL INJURY, DEATH, OR SEVERE PROPERTY OR ENVIRONMENTAL DAMAGE. ST PRODUCTS WHICH ARE NOT SPECIFIED AS "AUTOMOTIVE GRADE" MAY ONLY BE USED IN AUTOMOTIVE APPLICATIONS AT USER'S OWN RISK.

Resale of ST products with provisions different from the statements and/or technical features set forth in this document shall immediately void any warranty granted by ST for the ST product or service described herein and shall not create or extend in any manner whatsoever, any liability of ST.

ST and the ST logo are trademarks or registered trademarks of ST in various countries.

Information in this document supersedes and replaces all information previously supplied.

The ST logo is a registered trademark of STMicroelectronics. All other names are the property of their respective owners.

© 2009 STMicroelectronics - All rights reserved

STMicroelectronics group of companies

Australia - Belgium - Brazil - Canada - China - Czech Republic - Finland - France - Germany - Hong Kong - India - Israel - Italy - Japan - Malaysia - Malta - Morocco - Singapore - Spain - Sweden - Switzerland - United Kingdom - United States of America

www.st.com

477