

Electrical Spec REV D

Functional Description:

The STL1033-001 provides both safety and battery management functions for 1-cell Lithium Ion battery packs. In addition to preventing overvoltage during charge mode, undervoltage during discharge mode, and overcurrent during discharge mode, the STL1033-001 actively regulates charge current and voltage to ensure optimal battery charging.

Board Specifications

Board Dimensions:	See Drawing# 03-42584-01
Composition:	FR-4, double-sided, 1 oz copper
Connector:	Hirose A4B-3S-2C connector,
	A3B-2630SCC terminal
Assembly:	PCBA solder operation utilizes no-clean flux. No
	secondary cleaning operation performed.
Testing:	Testing performed per IPS-02584-001

Temperature

Operating Temperature:	-20 to 60 °C
Storage Temperature:	-40 to 125 °C

Electrical Specifications at Ta = 25 °C (per cell)

Parameter	Conditions	Min	Typical	Max	Units
		. ==			
Supply voltage	No Load	4.75	5.7	6.2	V
Overdischarge detection voltage		2.3	2.4	2.5	V
Sleep-mode recovery voltage *			1.5		V
Overcharge detection voltage		4.245	4.295	4.345	V
Regulated charge voltage		4.10	4.15	4.26	V
Regulated charge current		250	290	322	mA
Maximum discharge current	Continuous	3.0			A
	(4V cell voltage)				
Maximum discharge current	10 ms pulse, 1%			10.0	A
-	Duty Cycle				
Quiescent Current	Vcell < 2.3Vdc		50uA		uA
Quiescent Current	Vcell > 2.3Vdc		200uA		uA

* STL1033-001 will still attempt recovery below this voltage.

Disclaimer:


ICC will not be held responsible when used outside of the recommended parameters / applications.

Avoid excessive heat when soldering to the PCB.

Product is tested 100% at the factory. As with all good manufacturing practices, we also recommend 100% testing in the end product. Questions should be directed to ICC Technical Staff 312-829-2525



Connection Diagram



PAD Designations

BH+	Cell (+)
BG-	Cell (-)
PH+	Charger (+) (red wire)
PG-	Charger/Load (-) (black wire)
LH+	Load (+) (blue wire or alt per
	drawing 03-42584-01)


STL1033-001 Features

- Charge voltage and current regulation-allows use of unregulated power supplies to • charge Li-lon battery
- Built-in Safety Circuit functions to protect battery: •
- Overvoltage during Charge Mode
- Undervoltage during Discharge Mode
- Overcurrent during Discharge Mode
- Independent charge and discharge terminals allow for simultaneous battery charging • and powering of load.
- Small circuit footprint can be used with majority of prismatic and cylindrical Li-lon • batteries

Typical Applications

- 1-cell Lithium Ion battery packs
- Video cameras
- Misc. portable products

Disclaimer: ICC will not be held responsible when used outside of the recommended parameters / applications. Avoid excessive heat when soldering to the PCB. Product is tested 100% at the factory. As with all good manufacturing practices, we also recommend 100% testing in the end product. Questions should be directed to ICC Technical Staff 312-829-2525



7		8			
RIPTION	DATE	ΒY	СНК	APP	
JCTION	02/09/01	HG	KE		
IENTION 5.5MM	03/19/01	HG	KE		
5 TO 80.5±1.5	03/19/01	HG	KE		
	03/19/01	HG	KE		А
RE COLOR FOR BLUE WIR		HG	KE		
	03/19/01	HG	KE		
DETAIL I 2:1		AX.			В
E,ICC DOCUMENT					С
INSIDE OUTER CANT.	ONAL COMPONE TERNATIONAL	INTS C	DRP.,		D
	SUPERSEDES				
IMETERS	DATED				
 I.R. SHARP C⊡RNER S 1UM = 1/10 MM ³		RICA ERN4 ITED	4 <i>TIO</i> I		
	19 ON SU Shatin,n Hong Ro	N STREET EV TEABIT NG.	gates,		Е
NIT W/CHARGE	2584				
	A3 03-4	she 2584			
7		8			